



Einbaudownlight aus Aluminiumdruckguss
Feinstrukturlack in Weiß, Schwarz oder Silber matt
BASIC Reflektor in 5 Ausstrahlwinkel
Strahlerelement 350° drehbar und 30° schwenkbar

Aluminium downlighter
Microstructure painting in white, black or silver matt
BASIC reflector in 5 beam angles
350° swiveling and 30° tilting

Incasso in alluminio
Verniciato bianco, nero o grigio opaco
BASIC riflettore in 5 fasci di emissione
Girevole a 350°, orientabile a 30°

Encassé à LED en aluminium
Peinture en microstructure en blanc, noir ou argent mat
BASIC réflecteurs en 5 faisceaux disponibles
Pivotant à 350 et inclinaison de 30°

MOVA Konfigurator: www.moltoluca.com

Detailinfo Smart Bluetooth: Seite/page 532

IP 20

Lumenwerte ohne Glas
Lumen values without glass

MOVA M TURN BASIC R

Binning SDCM 3 exkl. Konverter / excl. converter

Power feed	350mA - 12W			500mA - 17W			700mA - 24W			800mA - 28W		
	lm W2	lm W3	lm W4	lm W2	lm W3	lm W4	lm W2	lm W3	lm W4	lm W2	lm W3	lm W4
Order converter not dimm.	24-127530n			24-127532n			24-127534n			24-127484n		
Order converter Dali dimm.	24-127490			24-127490			24-127490			24-127490		
Order conv. BLUETOOTH dimm.	701-1001			701-1001			701-1001			701-1001		
695-51C0012WWXX0	1280	1500	1580	1760	2070	2170	2360	2770	2900	2640	3100	3250
695-51C0013WWXX0	1280	1500	1580	1760	2070	2170	2360	2770	2900	2640	3100	3250
695-51C0014WWXX0	1280	1500	1580	1760	2070	2170	2360	2770	2900	2640	3100	3250
695-51C0015WWXX0	1280	1500	1580	1760	2070	2170	2360	2770	2900	2640	3100	3250
695-51C0016WWXX0	1280	1500	1580	1760	2070	2170	2360	2770	2900	2640	3100	3250

Power feed	900mA - 29W			1050mA - 35W		
	lm W2	lm W3	lm W4	lm W2	lm W3	lm W4
Order converter not dimm.	24-127536n			24-127538n		
Order converter Dali dimm.	24-127490			24-127490		
Order conv. BLUETOOTH dimm.	701-1001			701-1001		
695-51C0913WWXX0	3100	3640	3820	3490	4100	4300
695-51C0914WWXX0	3100	3640	3820	3490	4100	4300

ARTIKELNUMMER ERGÄNZEN / COMPLETE CODE

C = COVER	W = LICHTFARBE/LIGHT COLOUR	XX = FARBE/COLOUR
without glass = 0	LED 2700K = 43 PREMIUM CRI >90	silver matt = 44
with glass = 1	LED 3000K = 49 PREMIUM CRI >90	white = 55
	LED 4000K = 24 CRI >90	black = 66

LED CONVERTER MOVA M TURN BASIC R

Code	W	Control	Current	Dimensions
24-127530n		schaltbar/switchable	for 350mA	L 146 x B 44 x H 30mm
24-127532n		schaltbar/switchable	for 500mA	L 146 x B 44 x H 30mm
24-127534n		schaltbar/switchable	for 700mA	L 146 x B 44 x H 30mm
24-127484n		schaltbar/switchable	for 800mA	L 146 x B 44 x H 30mm
24-127536n		schaltbar/switchable	for 900mA	L 146 x B 44 x H 30mm
24-127538n		schaltbar/switchable	for 1050mA	L 146 x B 44 x H 30mm
24-127490		DALI Dimm.	for 300 - 1050mA	L 146 x B 44 x H 30mm
701-1001		SMART BLUETOOTH Dimm.	for 350 - 1200mA	L 129 x B 76 x H 30mm

Einbaudownlight aus Aluminiumdruckguss
Feinstrukturlack in Weiß, Schwarz oder Silber matt
HIGH EFFICIENCY Reflektor in 3 Ausstrahlwinkel
Strahlerelement 350° drehbar und 30° schwenkbar

Die cast Aluminium downlighter
Microstructure painting in white, black or silver matt
HIGH EFFICIENCY reflector in 3 beam angles
350° swiveling and 30° tilting

Incasso in alluminio pressofuso
Verniciato bianco, nero o grigio opaco
HIGH EFFICIENCY riflettore in 3 fasci di emissione
Girevole a 350°, orientabile a 30°

Encassé à LED en aluminium
Peinture en microstructure en blanc, noir ou argent mat
HIGH EFFICIENCY réflecteurs en 3 faisceaux disponibles
Pivotant à 350 et inclinaison de 30°

MOVA Konfigurator: www.moltoluca.com

Detailinfo Smart Bluetooth: Seite/page 532

IP 20

Lumenwerte ohne Glas
Lumen values without glass

MOVA M TURN HIGH EFFICIENCY R

Binning SDCM 3 exkl. Konverter / excl. converter

Power feed	350mA - 12W			500mA - 17W			700mA - 24W			800mA - 28W		
	lm W2	lm W3	lm W4	lm W2	lm W3	lm W4	lm W2	lm W3	lm W4	lm W2	lm W3	lm W4
Order converter not dimm.	24-127530n			24-127532n			24-127534n			24-127484n		
Order converter Dali dimm.	24-127490			24-127490			24-127490			24-127490		
Order conv. BLUETOOTH dimm.	701-1001			701-1001			701-1001			701-1001		
695-51C0023WWXX0	1380	1630	1700	1910	2240	2350	2550	3000	3140	2860	3360	3520
695-51C0024WWXX0	1380	1630	1700	1910	2240	2350	2550	3000	3140	2860	3360	3520
695-51C0025WWXX0	1380	1630	1700	1910	2240	2350	2550	3000	3140	2860	3360	3520

Power feed	900mA - 29W			1050mA - 35W		
	lm W2	lm W3	lm W4	lm W2	lm W3	lm W4
Order converter not dimm.	24-127536n			24-127538n		
Order converter Dali dimm.	24-127490			24-127490		
Order conv. BLUETOOTH dimm.	701-1001			701-1001		
695-51C0923WWXX0	3350	3940	4130	3780	4440	4650
695-51C0924WWXX0	3350	3940	4130	3780	4440	4650
695-51C0925WWXX0	3350	3940	4130	3780	4440	4650

ARTIKELNUMMER ERGÄNZEN / COMPLETE CODE

C = COVER	W = LICHTFARBE/LIGHT COLOUR	XX = FARBE/COLOUR
without glass = 0	LED 2700K = 43 PREMIUM CRI >90	silver matt = 44
with glass = 1	LED 3000K = 49 PREMIUM CRI >90	white = 55
	LED 4000K = 24 CRI >90	black = 66

LED CONVERTER MOVA M TURN HIGH EFFICIENCY R

Code	W	Control	Current	Dimensions
24-127530n		schaltbar/switchable	for 350mA	L 146 x B 44 x H 30mm
24-127532n		schaltbar/switchable	for 500mA	L 146 x B 44 x H 30mm
24-127534n		schaltbar/switchable	for 700mA	L 146 x B 44 x H 30mm
24-127484n		schaltbar/switchable	for 800mA	L 146 x B 44 x H 30mm
24-127536n		schaltbar/switchable	for 900mA	L 146 x B 44 x H 30mm
24-127538n		schaltbar/switchable	for 1050mA	L 146 x B 44 x H 30mm
24-127490		DALI Dimm.	for 300 - 1050mA	L 146 x B 44 x H 30mm
701-1001		SMART BLUETOOTH Dimm.	for 350 - 1200mA	L 129 x B 76 x H 30mm