

Installation Instructions

3 Circuit Track

Product information

SKU	Wattage	Dimension A/B/C/D mm	Weight
F3-15CT	15W	208/127/65/252	0.5Kg
F3-25CT	25W	239/157/80/252	0.75Kg
F3-35CT	35W	243/167/100/252	0.95Kg

Product Specification					Circuit Breaker Specification							
Model	Inrush current(A)	Inrush time	Rated Voltage (AC/V)	Input current (A)	B10	B13	B16	B20	C10	C13	C16	C20
F3-15CT	3.32A	37uS	AC220-240V	0.075	88	115	142	177	88	115	142	177
F3-25CT / F3-35CT	4.14A	48.9uS	AC220-240V	0.176	37	49	60	75	37	49	60	75

Regulations

To ensure correct functionality and safety, please read instructions carefully before installing the product. This luminaire complies with AS/NZS 60598.2.1

All wiring and installation of this luminaire must adhere to local and national wiring regulations eg AS/NZS 3000:2007 Amendment 2:2012 Electrical Installation

Tips

1. Always ensure power is off and the fitting has cooled down before performing any maintenance or adjustment to the fitting
2. To avoid injury or damage to the fitting, ensure that power leads and screws are secure before connecting the power
3. Handle the fitting with care to avoid damage/ breakage
4. Find a suitable location away from liquids or hazards
5. To clean, wipe with a damp clean cloth. Never soak the fitting with water.

WARNING

1. Switch off power supply before installation/maintenance.
2. Switch on only after complete installation and examination of the circuit.
3. Professional electrician for installation and maintenance only.



Standard Installation

